

# THORGEON

TIMERS

## DIGITAL TIMER SOCKET

18002



Manufactured in PRC



**W<sup>max</sup>**  
3680

**V**  
230V

**Hz**  
50

**A**  
16

**IP20**

**DISPLAY**

**NiMh 1.2V**

**-20°C**

**+40°C**

**180g**

# THORGEON



[www.thorgeon.com](http://www.thorgeon.com)

SIA "ATTA-1", Daugavgrivas street 77,  
Riga, Latvia, LV-1007



4751029898777  
Developed in Latvia

## 1. Features

Clock display, 10 sets of adjustable timed power control, randomized power control, manual switch and optional DST setup.

## 2. First time charging

This timer contains a rechargeable battery. It is normal that the new/old model runs out of battery if it wasn't being charged for a long period of time. In this case, the screen will not turn on. To charge : simply plug the timer to a power outlet. The charging time should take at least 15 minutes. If the screen doesn't light up or displays garbled characters, simply reboot the system by pressing the "RESET" button.

## 3. Set clock



Hold "CLOCK" button and "WEEK" button to adjust week.

Hold "CLOCK" button and "HOUR" button to adjust hour.

Hold "CLOCK" button and "MINUTE" button to adjust minute.

Hold "CLOCK" button and "TIMER" button to select 12 hour/24 hour display.

Hold "CLOCK" button and "ON/AUTO/OFF" button to enable/disable DST (daylight-saving-time).

## 4. Set timer


Press "TIMER" button, select and set timer. Setting rotation : 1on, 1off, 2on, 2off, 10off.

Press "HOUR" button to set hour for timer.

Press "MIN" button to set minute for timer.



Press "WEEK" button to set weekday for timer. Multiple weekdays can be selected. ex: if selected "MO", the timer will only apply on every Monday; if selected "MO, WE, FR", the timer will apply on every Monday, Wednesday and Friday.



Press "RES/RCL" button to cancel the selected on or off timer. The screen will show "-- : --", the timer is canceled. Press "RES/RCL" button again to reactivate the timer. When timers are set, press "CLOCK" to quit timer setting and return to clock.