



# **BR/R LED**

## PILA LED 75W A60 E27 WW FR ND 1CT/6 G3

Philips BR Dimmable LED Lamps with AirFlux technology provide a soft, diffused level of light and smooth dimming to reduce glare. The sleek, lightweight design is ideal for downlighting.

#### **Product data**

General Information	
Cap-Base	E27 [ E27]
EU RoHS compliant	Yes
Nominal Lifetime (Nom)	15000 h
Switching Cycle	30000X
Light Technical	
Color Code	827 [ CCT of 2700K]
Beam Angle (Nom)	180 °
Luminous Flux (Nom)	1055 lm
Color Designation	Warm White (WW)
Correlated Color Temperature (Nom)	2700 K
Luminous Efficacy (rated) (Nom)	105.00 lm/W
Color Consistency	<6
Color Rendering Index (Nom)	80
LLMF At End Of Nominal Lifetime (Nom)	70 %

Power Factor (Nom)	0.54
Voltage (Nom)	220-240 V
Temperature	
T-Case Maximum (Nom)	95 ℃
Controls and Dimming	
Dimmable	No
Mechanical and Housing	
Bulb Finish	Frosted
Bulb Shape	A60 [ A 60mm]
Approval and Application	
Energy Efficiency Label (EEL)	F
Energy Consumption kWh/1000 h	10 kWh
Product Data	
Full product code	872790096862000
Order product name	PILA LED 75W A60 E27 WW FR ND 1CT/6 G3
EAN/UPC - Product	8727900968620
Order code	929002306531
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	6

#### **Operating and Electrical**

operating and Electricat	
Input Frequency	50 to 60 Hz
Power (Nom)	10 W
Lamp Current (Nom)	90 mA
Wattage Equivalent	75 W
Starting Time (Nom)	0.4 s
Warm Up Time to 60% Light (Nom)	0.4 s

### **BR/R LED**

Material Nr. (12NC)	929002306531
Net Weight (Piece)	10.000 g



© 2021 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. All trademarks are owned by Signify Holding or their respective owners.

www.lighting.philips.com 2021, August 5 - data subject to change